

[Name of Document] SPECIFICATION

[Title of the Invention] DRIVING METHOD FOR ELECTRO-OPTICAL DEVICE,  
ELECTRO-OPTICAL DEVICE, AND ELECTRONIC APPARATUS

[Claims]

5487  
00000004.092101  
[Claim 1] A driving method for an electro-optical device which comprises, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor, the driving method comprising:

a setting step of supplying a first on-signal to the switching transistor via the scanning line, and of supplying a set signal for selecting a conducting state or a non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the first on-signal is supplied; and

a resetting step of supplying a second on-signal to the switching transistor via the scanning line, and of supplying a reset signal for selecting the non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the second on-signal is supplied.

[Claim 2] A driving method for an electro-optical device according to claim 1, wherein a horizontal scanning period comprises a first sub horizontal scanning period for performing the setting step and a second sub horizontal scanning period for performing the resetting step.

[Claim 3] A driving method for an electro-optical device according to

SUB B1  
SUB A1  
SUB A2  
SUB A3  
SUB A4  
SUB A5  
SUB A6  
SUB A7  
SUB A8  
SUB A9  
SUB A10  
SUB A11  
SUB A12  
SUB A13  
SUB A14  
SUB A15  
SUB A16  
SUB A17  
SUB A18  
SUB A19  
SUB A20  
SUB A21  
SUB A22  
SUB A23  
SUB A24  
SUB A25  
SUB A26  
SUB A27  
SUB A28  
SUB A29  
SUB A30  
SUB A31  
SUB A32  
SUB A33  
SUB A34  
SUB A35  
SUB A36  
SUB A37  
SUB A38  
SUB A39  
SUB A40  
SUB A41  
SUB A42  
SUB A43  
SUB A44  
SUB A45  
SUB A46  
SUB A47  
SUB A48  
SUB A49  
SUB A50  
SUB A51  
SUB A52  
SUB A53  
SUB A54  
SUB A55  
SUB A56  
SUB A57  
SUB A58  
SUB A59  
SUB A60  
SUB A61  
SUB A62  
SUB A63  
SUB A64  
SUB A65  
SUB A66  
SUB A67  
SUB A68  
SUB A69  
SUB A70  
SUB A71  
SUB A72  
SUB A73  
SUB A74  
SUB A75  
SUB A76  
SUB A77  
SUB A78  
SUB A79  
SUB A80  
SUB A81  
SUB A82  
SUB A83  
SUB A84  
SUB A85  
SUB A86  
SUB A87  
SUB A88  
SUB A89  
SUB A90  
SUB A91  
SUB A92  
SUB A93  
SUB A94  
SUB A95  
SUB A96  
SUB A97  
SUB A98  
SUB A99  
SUB A100  
SUB A101  
SUB A102  
SUB A103  
SUB A104  
SUB A105  
SUB A106  
SUB A107  
SUB A108  
SUB A109  
SUB A110  
SUB A111  
SUB A112  
SUB A113  
SUB A114  
SUB A115  
SUB A116  
SUB A117  
SUB A118  
SUB A119  
SUB A120  
SUB A121  
SUB A122  
SUB A123  
SUB A124  
SUB A125  
SUB A126  
SUB A127  
SUB A128  
SUB A129  
SUB A130  
SUB A131  
SUB A132  
SUB A133  
SUB A134  
SUB A135  
SUB A136  
SUB A137  
SUB A138  
SUB A139  
SUB A140  
SUB A141  
SUB A142  
SUB A143  
SUB A144  
SUB A145  
SUB A146  
SUB A147  
SUB A148  
SUB A149  
SUB A150  
SUB A151  
SUB A152  
SUB A153  
SUB A154  
SUB A155  
SUB A156  
SUB A157  
SUB A158  
SUB A159  
SUB A160  
SUB A161  
SUB A162  
SUB A163  
SUB A164  
SUB A165  
SUB A166  
SUB A167  
SUB A168  
SUB A169  
SUB A170  
SUB A171  
SUB A172  
SUB A173  
SUB A174  
SUB A175  
SUB A176  
SUB A177  
SUB A178  
SUB A179  
SUB A180  
SUB A181  
SUB A182  
SUB A183  
SUB A184  
SUB A185  
SUB A186  
SUB A187  
SUB A188  
SUB A189  
SUB A190  
SUB A191  
SUB A192  
SUB A193  
SUB A194  
SUB A195  
SUB A196  
SUB A197  
SUB A198  
SUB A199  
SUB A200  
SUB A201  
SUB A202  
SUB A203  
SUB A204  
SUB A205  
SUB A206  
SUB A207  
SUB A208  
SUB A209  
SUB A210  
SUB A211  
SUB A212  
SUB A213  
SUB A214  
SUB A215  
SUB A216  
SUB A217  
SUB A218  
SUB A219  
SUB A220  
SUB A221  
SUB A222  
SUB A223  
SUB A224  
SUB A225  
SUB A226  
SUB A227  
SUB A228  
SUB A229  
SUB A230  
SUB A231  
SUB A232  
SUB A233  
SUB A234  
SUB A235  
SUB A236  
SUB A237  
SUB A238  
SUB A239  
SUB A240  
SUB A241  
SUB A242  
SUB A243  
SUB A244  
SUB A245  
SUB A246  
SUB A247  
SUB A248  
SUB A249  
SUB A250  
SUB A251  
SUB A252  
SUB A253  
SUB A254  
SUB A255  
SUB A256  
SUB A257  
SUB A258  
SUB A259  
SUB A260  
SUB A261  
SUB A262  
SUB A263  
SUB A264  
SUB A265  
SUB A266  
SUB A267  
SUB A268  
SUB A269  
SUB A270  
SUB A271  
SUB A272  
SUB A273  
SUB A274  
SUB A275  
SUB A276  
SUB A277  
SUB A278  
SUB A279  
SUB A280  
SUB A281  
SUB A282  
SUB A283  
SUB A284  
SUB A285  
SUB A286  
SUB A287  
SUB A288  
SUB A289  
SUB A290  
SUB A291  
SUB A292  
SUB A293  
SUB A294  
SUB A295  
SUB A296  
SUB A297  
SUB A298  
SUB A299  
SUB A300  
SUB A301  
SUB A302  
SUB A303  
SUB A304  
SUB A305  
SUB A306  
SUB A307  
SUB A308  
SUB A309  
SUB A310  
SUB A311  
SUB A312  
SUB A313  
SUB A314  
SUB A315  
SUB A316  
SUB A317  
SUB A318  
SUB A319  
SUB A320  
SUB A321  
SUB A322  
SUB A323  
SUB A324  
SUB A325  
SUB A326  
SUB A327  
SUB A328  
SUB A329  
SUB A330  
SUB A331  
SUB A332  
SUB A333  
SUB A334  
SUB A335  
SUB A336  
SUB A337  
SUB A338  
SUB A339  
SUB A340  
SUB A341  
SUB A342  
SUB A343  
SUB A344  
SUB A345  
SUB A346  
SUB A347  
SUB A348  
SUB A349  
SUB A350  
SUB A351  
SUB A352  
SUB A353  
SUB A354  
SUB A355  
SUB A356  
SUB A357  
SUB A358  
SUB A359  
SUB A360  
SUB A361  
SUB A362  
SUB A363  
SUB A364  
SUB A365  
SUB A366  
SUB A367  
SUB A368  
SUB A369  
SUB A370  
SUB A371  
SUB A372  
SUB A373  
SUB A374  
SUB A375  
SUB A376  
SUB A377  
SUB A378  
SUB A379  
SUB A380  
SUB A381  
SUB A382  
SUB A383  
SUB A384  
SUB A385  
SUB A386  
SUB A387  
SUB A388  
SUB A389  
SUB A390  
SUB A391  
SUB A392  
SUB A393  
SUB A394  
SUB A395  
SUB A396  
SUB A397  
SUB A398  
SUB A399  
SUB A400  
SUB A401  
SUB A402  
SUB A403  
SUB A404  
SUB A405  
SUB A406  
SUB A407  
SUB A408  
SUB A409  
SUB A410  
SUB A411  
SUB A412  
SUB A413  
SUB A414  
SUB A415  
SUB A416  
SUB A417  
SUB A418  
SUB A419  
SUB A420  
SUB A421  
SUB A422  
SUB A423  
SUB A424  
SUB A425  
SUB A426  
SUB A427  
SUB A428  
SUB A429  
SUB A430  
SUB A431  
SUB A432  
SUB A433  
SUB A434  
SUB A435  
SUB A436  
SUB A437  
SUB A438  
SUB A439  
SUB A440  
SUB A441  
SUB A442  
SUB A443  
SUB A444  
SUB A445  
SUB A446  
SUB A447  
SUB A448  
SUB A449  
SUB A450  
SUB A451  
SUB A452  
SUB A453  
SUB A454  
SUB A455  
SUB A456  
SUB A457  
SUB A458  
SUB A459  
SUB A460  
SUB A461  
SUB A462  
SUB A463  
SUB A464  
SUB A465  
SUB A466  
SUB A467  
SUB A468  
SUB A469  
SUB A470  
SUB A471  
SUB A472  
SUB A473  
SUB A474  
SUB A475  
SUB A476  
SUB A477  
SUB A478  
SUB A479  
SUB A480  
SUB A481  
SUB A482  
SUB A483  
SUB A484  
SUB A485  
SUB A486  
SUB A487  
SUB A488  
SUB A489  
SUB A490  
SUB A491  
SUB A492  
SUB A493  
SUB A494  
SUB A495  
SUB A496  
SUB A497  
SUB A498  
SUB A499  
SUB A500  
SUB A501  
SUB A502  
SUB A503  
SUB A504  
SUB A505  
SUB A506  
SUB A507  
SUB A508  
SUB A509  
SUB A510  
SUB A511  
SUB A512  
SUB A513  
SUB A514  
SUB A515  
SUB A516  
SUB A517  
SUB A518  
SUB A519  
SUB A520  
SUB A521  
SUB A522  
SUB A523  
SUB A524  
SUB A525  
SUB A526  
SUB A527  
SUB A528  
SUB A529  
SUB A530  
SUB A531  
SUB A532  
SUB A533  
SUB A534  
SUB A535  
SUB A536  
SUB A537  
SUB A538  
SUB A539  
SUB A540  
SUB A541  
SUB A542  
SUB A543  
SUB A544  
SUB A545  
SUB A546  
SUB A547  
SUB A548  
SUB A549  
SUB A550  
SUB A551  
SUB A552  
SUB A553  
SUB A554  
SUB A555  
SUB A556  
SUB A557  
SUB A558  
SUB A559  
SUB A560  
SUB A561  
SUB A562  
SUB A563  
SUB A564  
SUB A565  
SUB A566  
SUB A567  
SUB A568  
SUB A569  
SUB A570  
SUB A571  
SUB A572  
SUB A573  
SUB A574  
SUB A575  
SUB A576  
SUB A577  
SUB A578  
SUB A579  
SUB A580  
SUB A581  
SUB A582  
SUB A583  
SUB A584  
SUB A585  
SUB A586  
SUB A587  
SUB A588  
SUB A589  
SUB A590  
SUB A591  
SUB A592  
SUB A593  
SUB A594  
SUB A595  
SUB A596  
SUB A597  
SUB A598  
SUB A599  
SUB A600  
SUB A601  
SUB A602  
SUB A603  
SUB A604  
SUB A605  
SUB A606  
SUB A607  
SUB A608  
SUB A609  
SUB A610  
SUB A611  
SUB A612  
SUB A613  
SUB A614  
SUB A615  
SUB A616  
SUB A617  
SUB A618  
SUB A619  
SUB A620  
SUB A621  
SUB A622  
SUB A623  
SUB A624  
SUB A625  
SUB A626  
SUB A627  
SUB A628  
SUB A629  
SUB A630  
SUB A631  
SUB A632  
SUB A633  
SUB A634  
SUB A635  
SUB A636  
SUB A637  
SUB A638  
SUB A639  
SUB A640  
SUB A641  
SUB A642  
SUB A643  
SUB A644  
SUB A645  
SUB A646  
SUB A647  
SUB A648  
SUB A649  
SUB A650  
SUB A651  
SUB A652  
SUB A653  
SUB A654  
SUB A655  
SUB A656  
SUB A657  
SUB A658  
SUB A659  
SUB A660  
SUB A661  
SUB A662  
SUB A663  
SUB A664  
SUB A665  
SUB A666  
SUB A667  
SUB A668  
SUB A669  
SUB A670  
SUB A671  
SUB A672  
SUB A673  
SUB A674  
SUB A675  
SUB A676  
SUB A677  
SUB A678  
SUB A679  
SUB A680  
SUB A681  
SUB A682  
SUB A683  
SUB A684  
SUB A685  
SUB A686  
SUB A687  
SUB A688  
SUB A689  
SUB A690  
SUB A691  
SUB A692  
SUB A693  
SUB A694  
SUB A695  
SUB A696  
SUB A697  
SUB A698  
SUB A699  
SUB A700  
SUB A701  
SUB A702  
SUB A703  
SUB A704  
SUB A705  
SUB A706  
SUB A707  
SUB A708  
SUB A709  
SUB A710  
SUB A711  
SUB A712  
SUB A713  
SUB A714  
SUB A715  
SUB A716  
SUB A717  
SUB A718  
SUB A719  
SUB A720  
SUB A721  
SUB A722  
SUB A723  
SUB A724  
SUB A725  
SUB A726  
SUB A727  
SUB A728  
SUB A729  
SUB A730  
SUB A731  
SUB A732  
SUB A733  
SUB A734  
SUB A735  
SUB A736  
SUB A737  
SUB A738  
SUB A739  
SUB A740  
SUB A741  
SUB A742  
SUB A743  
SUB A744  
SUB A745  
SUB A746  
SUB A747  
SUB A748  
SUB A749  
SUB A750  
SUB A751  
SUB A752  
SUB A753  
SUB A754  
SUB A755  
SUB A756  
SUB A757  
SUB A758  
SUB A759  
SUB A760  
SUB A761  
SUB A762  
SUB A763  
SUB A764  
SUB A765  
SUB A766  
SUB A767  
SUB A768  
SUB A769  
SUB A770  
SUB A771  
SUB A772  
SUB A773  
SUB A774  
SUB A775  
SUB A776  
SUB A777  
SUB A778  
SUB A779  
SUB A780  
SUB A781  
SUB A782  
SUB A783  
SUB A784  
SUB A785  
SUB A786  
SUB A787  
SUB A788  
SUB A789  
SUB A790  
SUB A791  
SUB A792  
SUB A793  
SUB A794  
SUB A795  
SUB A796  
SUB A797  
SUB A798  
SUB A799  
SUB A800  
SUB A801  
SUB A802  
SUB A803  
SUB A804  
SUB A805  
SUB A806  
SUB A807  
SUB A808  
SUB A809  
SUB A810  
SUB A811  
SUB A812  
SUB A813  
SUB A814  
SUB A815  
SUB A816  
SUB A817  
SUB A818  
SUB A819  
SUB A820  
SUB A821  
SUB A822  
SUB A823  
SUB A824  
SUB A825  
SUB A826  
SUB A827  
SUB A828  
SUB A829  
SUB A830  
SUB A831  
SUB A832  
SUB A833  
SUB A834  
SUB A835  
SUB A836  
SUB A837  
SUB A838  
SUB A839  
SUB A840  
SUB A841  
SUB A842  
SUB A843  
SUB A844  
SUB A845  
SUB A846  
SUB A847  
SUB A848  
SUB A849  
SUB A850  
SUB A851  
SUB A852  
SUB A853  
SUB A854  
SUB A855  
SUB A856  
SUB A857  
SUB A858  
SUB A859  
SUB A860  
SUB A861  
SUB A862  
SUB A863  
SUB A864  
SUB A865  
SUB A866  
SUB A867  
SUB A868  
SUB A869  
SUB A870  
SUB A871  
SUB A872  
SUB A873  
SUB A874  
SUB A875  
SUB A876  
SUB A877  
SUB A878  
SUB A879  
SUB A880  
SUB A881  
SUB A882  
SUB A883  
SUB A884  
SUB A885  
SUB A886  
SUB A887  
SUB A888  
SUB A889  
SUB A890  
SUB A891  
SUB A892  
SUB A893  
SUB A894  
SUB A895  
SUB A896  
SUB A897  
SUB A898  
SUB A899  
SUB A900  
SUB A901  
SUB A902  
SUB A903  
SUB A904  
SUB A905  
SUB A906  
SUB A907  
SUB A908  
SUB A909  
SUB A910  
SUB A911  
SUB A912  
SUB A913  
SUB A914  
SUB A915  
SUB A916  
SUB A917  
SUB A918  
SUB A919  
SUB A920  
SUB A921  
SUB A922  
SUB A923  
SUB A924  
SUB A925  
SUB A926  
SUB A927  
SUB A928  
SUB A929  
SUB A930  
SUB A931  
SUB A932  
SUB A933  
SUB A934  
SUB A935  
SUB A936  
SUB A937  
SUB A938  
SUB A939  
SUB A940  
SUB A941  
SUB A942  
SUB A943  
SUB A944  
SUB A945  
SUB A946  
SUB A947  
SUB A948  
SUB A949  
SUB A950  
SUB A951  
SUB A952  
SUB A953  
SUB A954  
SUB A955  
SUB A956  
SUB A957  
SUB A958  
SUB A959  
SUB A960  
SUB A961  
SUB A962  
SUB A963  
SUB A964  
SUB A965  
SUB A966  
SUB A967  
SUB A968  
SUB A969  
SUB A970  
SUB A971  
SUB A972  
SUB A973  
SUB A974  
SUB A975  
SUB A976  
SUB A977  
SUB A978  
SUB A979  
SUB A980  
SUB A981  
SUB A982  
SUB A983  
SUB A984  
SUB A985  
SUB A986  
SUB A987  
SUB A988  
SUB A989  
SUB A990  
SUB A991  
SUB A992  
SUB A993  
SUB A994  
SUB A995  
SUB A996  
SUB A997  
SUB A998  
SUB A999  
SUB A1000

[Claim 4] A driving method for an electro-optical device according to any one of claims 1 to 3, wherein a gray-scale is obtained by performing a plurality of set-reset operations, each set-reset operation comprising the setting step and the resetting step.

[Claim 5] A driving method for an electro-optical device according to claim 4, wherein a time interval between the setting step and the resetting step is different for each of the plurality of set-reset operations.

[Claim 6] A driving method for an electro-optical device according to one of claims 4 and 5, wherein the time interval between the setting step and the resetting step for each of the plurality of set-reset operations is completely different from each other, and the ratio of time intervals for the plurality of set-reset operations is set to be about 1:2: .. :2<sup>n</sup> (n is an integer of one or more) based on the minimum time interval.

[Claim 7] A driving method for an electro-optical device according to any one of claims 1 to 6, wherein the set signal is a signal for setting the conducting state for the driving transistor rather than the signal for selecting the conducting state or the non-conducting state of the driving transistor.

[Claim 8] A driving method for an electro-optical device according to any one of claims 1 to 7, wherein the electro-optical element comprises

an organic electro-luminescence element.

[Claim 9] An electro-optical device driven by the driving method set forth in any one of claims 1 to 8.

[Claim 10] An electro-optical device including, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor, the electro-optical device comprising a drive circuit for generating a signal for setting the switching transistor to be an on-state or an off-state, and for generating a signal for setting or resetting the driving transistor in accordance with the signal for setting the switching transistor to be the on-state or the off-state.

[Claim 11] An electro-optical device including, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor, the electro-optical device comprising:

a scanning line driver for supplying a signal for setting the switching transistor to be an on-state or an off-state to the scanning line; and

a data line driver for supplying a signal for setting or resetting the driving transistor to the data line in accordance with an operation of the scanning line driver.

[Claim 12] An electro-optical device comprising, at an intersection of a scanning line and a data line, an electro-optical element, a

503  
Ble

driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor,

wherein an on-signal for performing a setting step of setting the electro-optical element and a resetting step of resetting the electro-optical element is supplied to the switching transistor via the scanning line.

519  
30

[Claim 13] An electro-optical device according to any one of claims 10 to 12, wherein the electro-optical element comprises an organic electro-luminescence element.

[Claim 14] An electronic apparatus in which the electro-optical device set forth in any one of claims 9 to 13 is installed.

[Detailed Description of the Invention]

[Technical Field of the Invention]

FOR 260-466930

The present invention relates to a driving method for an organic electro-luminescence display device, a driving method for an electro-optical device suitable for use with an organic electro-luminescence display device the electro-optical device, and an electronic apparatus provided with such an electro-optical device.

[Description of the Related Art]

Attention is being given to organic electro-luminescence (electric-field luminescence) display devices using organic materials as luminescent materials of luminescent elements since they have a wide viewing angle, and will potentially meet market demands, i.e., demands for thinner, lighter, smaller, and lower power-consuming display devices.

Unlike conventional liquid crystal display devices, in organic

electro-luminescence display devices, the luminescence state of the luminescent element must be controlled by a current. One such control method is the conductance control method (T. Shimoda, M. Kimura, et al., Proc. Asia Display 98, 217; M. Kimura, et al., IEEE Trans. Ele. Dev. 46, 2282 (1999); M. Kimura, et al., Proc. IDW 99, 171; and M. Kimura et al., Dig. AM-LCD 2000, to be published). In this method, the luminescence state of the luminescent element is controlled by a current value, which is an analog value, and more specifically, it is controlled by changing the potential applied to a gate electrode of a driving transistor for driving the luminescent element. When thin-film transistors having different current characteristics are used, however, the difference in the current characteristics of the individual transistors may sometimes directly result in the non-uniformity in the luminescence state of the luminescent elements.

Accordingly, the area ratio gray-scale method (M. Kimura, et al., Proc. Euro Display '99 Late-News Papers, 71, Japanese Unexamined Patent Application Publication No. 11-073158, M. Kimura, et al., Proc. IDW 99, 171, M. Kimura, et al., J. SID, to be published; and M. Kimura, et al., Dig. AM-LCD 2000 to be published) has been proposed. In the area ratio gray-scale method, unlike the above-mentioned conductance control method, the luminescence state of the luminescent elements is controlled without using a luminescence state at an intermediate luminance. More specifically, in this method, a gray-scale is displayed as follows. Pixels disposed in a matrix are divided into a plurality of sub-pixels, and it is determined whether the luminescent elements contained in the

sub-pixels are either in a complete luminescence state or a complete non-luminescence state. Then, among the plurality of sub-pixels, the total area of the sub-pixels in the complete luminescence state is changed. In the area ratio gray-scale method, it is not necessary to set an intermediate current value corresponding to the luminescence state of the intermediate luminance. Accordingly, the influence of the current characteristics of the transistors for driving the luminescent elements can be reduced, thereby achieving a uniform image quality. In this method, however, the number of gray-scale levels is restricted by the number of sub-pixels. For a greater number of gray-scale levels, pixels must be divided into a greater number of sub-pixels, which makes the pixel structure complicated.

Accordingly, the time ratio gray-scale method (M. Kimura, et al., Proc. IDW 99, 171; M. Kimura, et al., Dig. AM-LCD 2000, to be published; M. Mizukami, et al., Dig. SID 2000, 912; and K. Inukai, et al., Dig. SID 2000, 924) has been proposed.

In the time ratio gray-scale method, the representation of the gray-scale is implemented by changing the period for which the luminescent elements in one frame are in the complete luminescence state. Accordingly, unlike the area ratio gray-scale method, it is not necessary to provide many sub-pixels for obtaining a greater number of gray-scale levels, and also, the time ratio gray-scale method can be used together with the area ratio gray-scale method. Thus, it is expected that the time ratio gray-scale method will be a promising method for digitally displaying a gray-scale.

## [Problems to be Solved by the Invention]

However, in the SES (Simultaneous-Erasing-Scan) time ratio gray-scale method, which is reported in "K. Inukai, et al., Dig. SID 2000,924", in addition to the scanning lines, reset lines are required, and thus, the luminescence area is disadvantageously reduced. Accordingly, a first object of the present invention is to provide a method for implementing the representation of a gray-scale of an electro-optical device without reset lines, and in particular, to provide a method for implementing the representation of the gray-scale of an electro-optical device, such as an organic electro-luminescence display device, according to the time ratio gray-scale method. A second object of the present invention is to provide an electro-optical device driven by the above-described driving method.

## [Means for Solving the Problems]

In order to achieve the first object, a first driving method for an electro-optical device according to the present invention is a driving method for an electro-optical device which includes, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor. The driving method includes: a setting step of supplying a first on-signal to the switching transistor via the scanning line, and of supplying a set signal for selecting a conducting state or a non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the first

on-signal is supplied; and a resetting step of supplying a second on-signal to the switching transistor via the scanning line, and of supplying a reset signal for selecting the non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the second on-signal is supplied.

With this arrangement, since the on-signal is supplied to the switching transistor via the scanning line, and the set signal or the reset signal is supplied via the data line in accordance with the on-signal, the state of the electro-optical element can be selected without a reset line. In this specification, the electro-optical element and the electro-optical device respectively indicate an element and a device in which the luminescence state or the optical characteristic is electrically controlled. Specific examples of the electro-optical device include display devices, such as luminescence display devices, liquid crystal display devices, and electrophoretic display devices.

Throughout the specification, the on-signal indicates a signal for selecting the on-state of the switching transistor. Also, throughout the specification, the "step of supplying a first on-signal to the switching transistor via the scanning line, and of supplying a set signal for selecting a conducting state or a non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the first on-signal is supplied" is defined as the "setting step". The "step of supplying a second on-signal to the switching transistor via the



scanning line, and of supplying a reset signal for selecting the non-conducting state of the driving transistor to the driving transistor via the data line and the switching transistor in accordance with a period for which the second on-signal is supplied" is defined as the "resetting step". The first on-signal and the second on-signal are not necessarily two consecutive on-signals, and may be discretely set.

A second driving method for an electro-optical device according to the present invention is characterized in that the horizontal scanning period may include a first sub horizontal scanning period for performing the setting step and a second sub horizontal scanning period for performing the resetting step. It is necessary that the first sub horizontal scanning period and the second sub horizontal scanning period be different from each other. Accordingly, the setting step and the resetting step do not overlap with each other. The first sub horizontal scanning period and the second sub horizontal scanning period are not necessarily two consecutive horizontal scanning periods, and may be discretely set. It is not necessary that the first sub horizontal scanning period and the second sub horizontal scanning period be included in the same horizontal scanning period, and may be included in different horizontal scanning periods.

According to a third driving method for an electro-optical device of the present invention, in the above-described driving method for an electro-optical device, the setting step may be performed in a first horizontal scanning period, and the resetting step may be performed in a second horizontal scanning period. It is necessary that the first sub

horizontal scanning period and the second sub horizontal scanning period be different from each other. Accordingly, the setting step and the resetting step do not overlap with each other. The setting step and the resetting step do not have to be performed throughout the whole horizontal scanning period, and may be partially performed in the horizontal scanning period. The first sub horizontal scanning period and the second sub horizontal scanning period are not necessarily two consecutive horizontal scanning periods, and may be discretely set.

According to a fourth driving method for an electro-optical device of the present invention, in the above-described driving method for an electro-optical device, a gray-scale may be obtained by performing a plurality of set-reset operations, each set-reset operation including the aforementioned setting step and the resetting step. Accordingly, the state of the electro-optical device is selected in the setting step, and remains the same until the resetting step is performed. Thus, by performing a plurality of set-reset operations, a gray-scale can be obtained. Throughout the specification, the set-reset operation is defined as an operation including the above-described setting step and the resetting step.

According to a fifth driving method for an electro-optical device of the present invention, in the above-described driving method for an electro-optical device, a time interval between the setting step and the resetting step may be different for each of the plurality of set-reset operations.

According to a sixth driving method for an electro-optical device

of the present invention, in the above-described driving method for an electro-optical device, the time interval between the setting step and the resetting step for each of the plurality of set-reset operations may be completely different from each other, and the ratio of time intervals for the plurality of set-reset operations may be about  $1:2: \dots :2^n$  ( $n$  is an integer of one or more). For example, if two set-reset operations with a time interval ratio of  $1:2$  are performed, four gray-scale levels, i.e., 0, 1, 2, 3, can be displayed. If two set-reset operations with a time interval ratio of  $1:1$  are performed, three gray-scale levels, i.e., 0, 1, and 2 can be displayed. That is, in this driving method for an electro-optical device, a maximum number of gray-scale levels can be obtained by a minimum number of set-reset operations. The time interval ratio does not have to be precisely  $1:2: \dots :2^n$  ( $n$  is an integer of one or more), and may be sufficient to such a degree to satisfy a required gray-scale precision.

According to a seventh driving method for an electro-optical device of the present invention, in the above-described driving method for an electro-optical device, the set signal may be a signal for setting the driving transistor to the conducting state rather than the signal for selecting the conducting state or the non-conducting state of the driving transistor. This means that an intermediate conducting state other than the two states, i.e., the conducting state and the non-conducting state, of the driving transistor is selectable. This can be implemented by the set signal provided as a voltage having three or more consecutive or discrete values. This driving method is effective for

implementing many gray-scale levels.

According to an eighth driving method for an electro-optical device of the present invention, in the above-described driving method for an electro-optical device, the electro-optical element may be an organic electro-luminescence element. Generally, the power consumption of the organic electro-luminescence element is advantageously low.

A first electro-optical device of the present invention is driven by the above-described driving method for an electro-optical device.

A second electro-optical device of the present invention is an electro-optical device including, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor. The electro-optical device includes a drive circuit for generating a signal for setting the switching transistor to be an on-state or an off-state, and for generating a signal for setting or resetting the driving transistor in accordance with the signal for setting the switching transistor to be the on-state or the off-state.

A third electro-optical device of the present invention is an electro-optical device including, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving the electro-optical element, and a switching transistor for controlling the driving transistor. The electro-optical device includes: a scanning line driver for supplying a signal for setting the switching transistor to be an on-state or an off-state to the scanning

line; and a data line driver for supplying a signal for setting or resetting the driving transistor to the data line in accordance with an operation of the scanning line driver.

A fourth electro-optical device of the present invention is an electro-optical device including, at an intersection of a scanning line and a data line, an electro-optical element, a driving transistor for driving this electro-optical element, and a switching transistor for controlling this driving transistor. In the fourth electro-optical device, an on-signal for performing a setting step of setting the electro-optical element and a resetting step of resetting the electro-optical element is supplied to the switching transistor via the scanning line. In the above description, the definitions of the setting step and the resetting step are substantially similar to those of the setting step and the resetting step set forth in claim 1. Accordingly, the first through fourth electro-optical devices of the present invention do not require a reset line for performing the time ratio gray-scale method. Advantageously, therefore, it is possible to ensure a sufficient area for the electro-optical element. If more gray-scale levels are required, the time ratio gray-scale method can be employed with the area ratio gray-scale method when sub pixels are provided in the pixels of the electro-optical device.

According to a fifth electro-optical device of the present invention, in the above-described electro-optical device, the electro-optical element may be an organic electro-luminescence element.

A first electronic apparatus of the present invention is an

electronic apparatus in which the above-described electro-optical device is installed.

[Description of the Embodiments]

Preferred embodiments of the present invention are described below.

A basic circuit used in an embodiment of the present invention includes a poly-crystal silicon thin-film transistor formed by a low-temperature process at 600°C or lower (low-temperature poly-Si TFT). The low-temperature poly-Si TFT can be formed on a large, inexpensive glass substrate, and can integrate a driving circuit on a panel, and accordingly, it is suitable for manufacturing an electro-optical device. Additionally, the low-temperature poly-Si TFT is small, but has a high current supplying power. Accordingly, it is suitable for use in a high-precision current luminescence display device. The present invention is also applicable to an electro-optical device driven by other types of transistors, such as an amorphous silicon thin-film transistor (a-Si TFT), a silicon-based transistor, and an organic thin-film transistor using an organic semiconductor.

The equivalent circuit of one pixel of an electro-optical device according to an embodiment of the present invention is shown in Fig. 1. In this embodiment, as the electro-optical element, a luminescent element is used. In this electro-optical device, a scanning line (S1), a data line (D1), and a power line (V) are formed, and a luminescent element (L11), a driving transistor (DT11) for driving the luminescent element (L11), a switching transistor (ST11) for controlling this driving transistor (DT11), and a capacitor (C11) are provided at the

intersection of the scanning line (S1) and the data line (D1). One end of the luminescent element (L11) is connected to an anode (A). The driving transistor (DT11) is p-type. Accordingly, the driving transistor (DT11) enters a conducting state selected by a low-potential data signal to cause the luminescent element (L11) to be in the luminescence state. In contrast, the driving transistor (DT11) enters a non-conducting state selected by a high-potential data signal to cause the luminescent element (L11) to be in the non-luminescence state. In the pixel equivalent circuit shown in Fig. 1, the switching transistor (ST11) is n-type, and the driving transistor (DT11) is p-type. However, this is not a limitation to implement the present invention.

Fig. 2 illustrates wiring and a pixel arrangement of an electro-optical device according to an embodiment of the present invention. Pixels are arranged in a matrix by a plurality of scanning lines (S1, S2, ....) and a plurality of data lines (D1, D2, ....), and a plurality of pixels are formed at corresponding intersections of the scanning lines and the data lines. For example, a pixel 11 is provided at the intersection of S1 and D1. Basically, the pixel includes a switching transistor (ST11), a capacitor (C11), a driving transistor (DT11), and a luminescent element (L11), such as those shown in Fig. 1. However, the pixel may include a plurality of sub-pixels. A power line is not shown in Fig. 2.

Fig. 3 illustrates a driving method for an electro-optical device according to an embodiment of the present invention. In this driving method, a horizontal scanning period (H) comprises two sub horizontal

scanning periods (SH1 and SH2). The scanning signal and the data signal are either a high-potential signal or a low-potential signal. A first scanning signal SS(S1) is supplied to the first scanning line (S1). A second scanning signal SS(S2) is supplied to the second scanning line (S2). A third scanning signal SS(S3) is supplied to the third scanning line (S3). A first data signal DS(D1) is supplied to the first data line (D1). A second data signal DS(D2) is supplied to the second data line (D2). A third data signal DS(D3) is supplied to the third data line (D3). In DS(D1), DS(D2), and DS(D3), the hatched portions indicate a set signal, while the other portions indicate a reset signal. A low-potential data signal, which causes the luminescent element to be in the luminescence state, is supplied as the set signal. For causing the luminescent element to be in the non-luminescence state, a high-potential set signal is supplied.

In the sub horizontal scanning period SH1 of the horizontal scanning period H1, the luminescent element is set to be in the luminescence state or the non-luminescence state by a setting step of "supplying a first on-signal to the switching transistor (ST11) via the scanning line (S1), and of supplying the set signal for selecting the conducting state or the non-conducting state of the driving transistor (DT11) to the driving transistor (DT11) via the data line D1 and the switching transistor (ST11) in accordance with the period for which the first on-signal is supplied". In the sub horizontal scanning period SH2 of the horizontal scanning period H2, the luminescent element is set to be in the non-luminescence state by a resetting step of "supplying a



second on-signal to the switching transistor (ST11) via the scanning line (S1), and of supplying the reset signal for selecting the non-conducting state of the driving transistor (DT11) to the driving transistor (DT11) via the data line D1 and the switching transistor (ST11) in accordance with the period for which the second on-signal is supplied". According to the above-described setting step and resetting step, the luminescence period (E1) of the first-row and first-column pixel 11 is set. It may take some time for the transistor or the luminescent element to respond to the corresponding signal. Accordingly, as shown in Fig. 3, the start time and the end time of the luminescence period may be displaced from the start of the setting step and the start of the resetting step, respectively. In Fig. 3, the period for which the first on-signal is supplied coincides with the period for which the set signal is supplied, and the period for which the second on-signal is supplied coincides with the period for which the reset signal is supplied. However, depending on the circumstances of the use or the specifications, the on-signal does not always have to coincide with the set signal or the reset signal.

The setting step and the resetting step for the subsequent scanning line (S2) are performed such that they are displaced from those for the scanning line (S1). As shown in Fig. 3, they are preferably performed at times closest to those for the scanning line (S1). Thereafter, similarly, the setting step and the resetting step are performed for the third scanning line (S3) and the subsequent scanning lines. Then, one vertical scanning period is finished. For the subsequent vertical

scanning period, the setting step and the resetting step are similarly performed for each scanning line. The ratio of the luminescence periods E1, E2, and E3 is about 1:2:4. As a result, eight gray-scale levels, such as 0, 1, 2, 3, 4, 5, 6, and 7, are obtained.

In the embodiment shown in Fig. 3, one horizontal scanning period is divided into two sub horizontal scanning periods. However, as shown in Fig. 4, the setting step and the resetting step may be set in units of horizontal scanning periods. In Fig. 4, the period of the setting step and the period of the resetting step respectively coincide with the horizontal scanning period. However, neither the setting step nor the resetting step has to be performed throughout the whole horizontal scanning period.

Among a plurality of set-reset operations, a set-reset operation may be partially or wholly performed during the same horizontal scanning period. Such an embodiment is shown in Fig. 5. In this embodiment, the setting step and the resetting step are performed in units of sub horizontal scanning periods (SH) which are obtained by dividing the horizontal scanning period (H) into four. The first set-reset operation is performed in the same horizontal scanning period. In the second and the subsequent set-reset operations, the horizontal scanning period of the sub horizontal scanning period for which the setting step is performed is different from that of the sub horizontal scanning period for which the resetting step is performed. In each vertical scanning period, upon completion of the horizontal scanning period for the first scanning line (S1), the set-reset operation is started for the second

In any of the driving methods for the electro-optical devices shown in Figs. 3 through 5, the set-reset operations are sequentially performed such that the time interval between the setting step and the resetting step is increased. However, the set-reset operations do not have to be performed in this order, and it can be performed according to the circumstances of the use or the specifications. As in the driving methods for the electro-optical devices shown in Figs. 3 through 5, for simplicity of a peripheral circuit system, such as a data line driver, the reset signal is preferably supplied at regular intervals. However, it is not essential that the reset signal be supplied at regular intervals, and the timing for supplying the on-signal and the reset signal to the switching transistor can suitably be set according to the desired luminescence period.

-19-

Fig. 7 illustrates a manufacturing process for a thin-film transistor for use in the electro-optical device according to an embodiment of the present invention. Amorphous silicon is first formed on a glass substrate 1 by PECVD using  $\text{SiH}_4$  or by LPCVD using  $\text{Si}_2\text{H}_6$ . The amorphous silicon is poly-crystallized by a laser, such as an excimer laser, or by solid-phase growth, thereby forming a poly-crystalline silicon layer 2 (Fig. 7(a)). After the poly-crystalline silicon layer 2 is patterned, a gate insulating film 3 is formed, and gate electrodes 4 are further formed (Fig. 7(b)). An impurity, such as phosphorus or boron, is implanted into the poly-crystalline silicon layer 2 by the gate electrodes 4 according to a self-alignment process so as to form MOS transistors 5a and 5b. The MOS transistors 5a and 5b are a p-type transistor and an n-type transistor, respectively. After a first interlayer insulating film 6 is formed, contact holes are formed, and a source electrode and a drain electrode 7 are formed (Fig. 7(c)). Then, after a second interlayer insulating film 8 is formed, contact holes are formed, and a pixel electrode 9 comprising ITO is formed (Fig. 7(d)).

-20-

electro-optical device according to an embodiment of the present invention. First, an adhesion layer 10 is formed, and an opening corresponding to a luminescent region is formed. An interlayer 11 is then formed, and an opening is formed (Fig. 8(a)). Then, the wettability of the substrate surface is controlled by performing plasma processing using, for example, oxygen plasma or  $CF_4$  plasma. Subsequently, an electron-hole implantation layer 12 and a luminescent layer 13 are formed according to a liquid-phase process, such as a spin coating, squeegee, or ink-jet process, or a vacuum process, such as sputtering or deposition. An anode 14 containing metal, such as aluminum, is then formed. Finally, a sealing layer 15 is formed. Thus, an organic electro-luminescence device is manufactured (Fig. 8(b)). The roles of the adhesion layer 10 are to improve the adhesion between the substrate and the interlayer 11 and also to obtain an accurate luminescence area. The roles of the interlayer 11 are to reduce the parasitic capacitance by separating the gate electrodes 4, the source electrodes, and the drain electrodes 7 from the anode 14, and also to perform precise patterning by controlling the surface wettability when forming the electron-hole implantation layer 12 and the luminescent layer 13 by a liquid-phase process.

Some examples of electronic apparatuses using the above-described electro-optical device are described below. Fig. 9 is a perspective view illustrating the configuration of a mobile personal computer to which the above-described electro-optical device is applied. In Fig. 9, a personal computer 1100 includes a main unit 1104 provided with a

keyboard 1102, and a display unit 1106. The display unit 1106 is provided with the above-described electro-optical device 100.

Fig. 10 is a perspective view illustrating the configuration of a cellular telephone having a display unit to which the aforementioned electro-optical device 100 is applied. In Fig. 10, a cellular telephone 1200 includes, not only a plurality of operation buttons 1202, but also the above-described electro-optical device 100 together with an earpiece 1204 and a mouthpiece 1206.

Fig. 11 is a perspective view illustrating the configuration of a digital still camera having a finder to which the above-described electro-optical device 100 is applied. Fig. 11 also schematically illustrates the connection of the digital still camera with external devices. In a regular camera, a film is exposed to light by an optical image of a subject. In a digital still camera 1300, however, an optical image of a subject is photoelectrically converted by an image pickup device, such as a CCD (Charge Coupled Device) so as to generate an imaging signal. On the rear surface of a casing 1302 of the digital still camera 1300, the aforementioned electro-optical device 100 is provided to display the subject based on the imaging signal obtained by the CCD. That is, the electro-optical device 100 serves as a finder for displaying the subject. On the observation side (on the reverse surface in Fig. 11) of the casing 1302, a photodetector unit 1304 including an optical lens and a CCD is disposed.

A photographer checks the subject displayed on the electro-optical device 100 and presses a shutter button 1306. Then, an imaging signal

obtained by the CCD is transferred to and stored in a memory of a circuit board 1308. In this digital still camera 1300, a video signal output terminal 1312 and a data communication input/output terminal 1314 are provided on the side surface of the casing 1302. Then, as shown in Fig. 11, a television monitor 1430 and a personal computer 1440 are connected to the video signal output terminal 1312 and the data communication input/output terminal 1314, respectively, as required. The imaging signal stored in the memory of the circuit board 1308 is output to the television monitor 1430 or the personal computer 1440 by a predetermined operation.

Electronic apparatuses to which the electro-optical device 100 of the present invention is applicable include, not only the personal computer shown in Fig. 9, the cellular telephone shown in Fig. 10, and the digital still camera shown in Fig. 11, but also a liquid crystal television, a view-finder-type or direct-view-type video cassette recorder, a car navigation system, a pager, an electronic diary, a calculator, a word processor, a workstation, a videophone, a POS terminal, a device provided with a touch panel, for example. It is needless to say that the above-described electro-optical device 100 is applicable to the display units of these electronic apparatuses.

[Brief Description of the Drawings]

[Fig. 1]

Fig. 1 illustrates a pixel equivalent circuit of an electro-optical device according to an embodiment of the present invention.

[Fig. 2]

Fig. 2 illustrates a pixel arrangement of an electro-optical device according to an embodiment of the present invention.

[Fig. 3]

Fig. 3 illustrates a driving method for an electro-optical apparatus according to an embodiment of the present invention.

[Fig. 4]

Fig. 4 illustrates a driving method for an electro-optical apparatus according to an embodiment of the present invention.

[Fig. 5]

Fig. 5 illustrates a driving method for an electro-optical apparatus according to an embodiment of the present invention.

[Fig. 6]

Fig. 6 illustrates the current characteristics of a luminescent element according to an embodiment of the present invention.

[Fig. 7]

Fig. 7 illustrates part of a manufacturing process for an electro-optical device according to an embodiment of the present invention.

[Fig. 8]

Fig. 8 illustrates part of a manufacturing process for an electro-optical device according to an embodiment of the present invention.

[Fig. 9]

Fig. 9 illustrates an example of an electro-optical device of an embodiment of the present invention applied to a mobile personal computer.

[Fig. 10]



Fig. 10 illustrates an example of an electro-optical device of an embodiment of the present invention applied to a display unit of a cellular telephone.

[Fig. 11]

Fig. 11 is a perspective view illustrating a digital still camera having a finder to which an electro-optical device of an embodiment of the present invention is applied.

[Reference Numerals]

V power line  
 A anode  
 L11 luminescent element  
 DT11 driving transistor  
 ST11 switching transistor  
 C11 capacitor  
 S1 first scanning line  
 S2 second scanning line  
 D1 first data line  
 D2 second data line  
 H horizontal scanning period  
 H1 first horizontal scanning period  
 H2 second horizontal scanning period  
 H3 third horizontal scanning period  
 H4 fourth horizontal scanning period  
 SH sub horizontal scanning period  
 SH1 first sub horizontal scanning period

SB2 second sub horizontal scanning period  
SS(S1) scanning signal for first scanning line  
SS(S2) scanning signal for second scanning line  
SS(S3) scanning signal for third scanning line  
DS(D1) data signal for first data line  
DS(D2) data signal for second data line  
DS(D3) data signal for third data line  
E1 first luminescence period of pixel 11  
E2 second luminescence period of pixel 11  
E3 third luminescence period of pixel 11  
Vsig control potential  
Ilep current value  
1 glass substrate  
2 poly-crystalline silicon layer  
3 gate insulating film  
4 gate electrode  
5a p-type transistor  
5b n-type transistor  
6 first interlayer insulating film  
7 source electrode and drain electrode  
8 second interlayer insulating film  
9 pixel electrode  
10 adhesion layer  
11 interlayer  
12 electron-hole implantation layer

F006304

13 luminescent layer

14 anode

15 sealing layer

0956994.092401